



Маслонаполненный предохранитель, среднее напряжение, 35.5 А, AC 12 kV, 40 кА, BS2692 F01, 63.5 x 254 mm, резерв, BS, IEC, ESI, с наклейкой, маслoneпроницаемый

Тип **12KV 35.5AMP 2.5" OIL FUSE**
Каталог № **120EFMA35.5**

Abbildung ähnlich

Программа поставок

| | | | |
|--|---|----|---|
| Программа поставок | | | Предохранитель |
| Основная функция | | | Маслонаполненный предохранитель |
| Область применения | | | среднее напряжение |
| Номинальный ток | I | A | 35.5 |
| Номинальное напряжение | | | AC 12 kV |
| Типоразмер | | | BS2692 F01 |
| Типоразмер | | | 63.5 x 254 mm |
| Категория применения | | | резерв |
| Индикатор состояния | | | с наклейкой |
| Описание | | | маслoneпроницаемый |
| Отключающая способность | | кА | 40 |
| возможно использование для типоразмеров/оборудования | | | защита первичной обмотки трансформатора и маслонаполненная комбинированная сборка выключателя с предохранителем |
| Стандарт/сертификат | | | BS IEC ESI |
| Форма | | | цилиндрический |
| Стандарты/предписания | | | BS2692-1 IEC 60282-1 ESI 12-8 |

Технические характеристики согласно ETIM 7.0

| | | | |
|--|--|----|-------------------------------------|
| Circuit breakers and fuses (EG000020) / Medium-/high voltage fuse (EC003507) | | | |
| Rated current | | A | 35.5 |
| Rated voltage | | kV | 12 |
| Voltage type | | | AC |
| Rated frequency | | Hz | 50 - 50 |
| Breaking capacity | | кА | 40 |
| Utilization category | | | Other |
| Application | | | Primary side transformer protection |
| Length | | mm | 254 |
| Diameter | | mm | 63.5 |
| Performance category according to IEC 60282-1 | | | Back-up |
| With striker | | | Yes |
| Standard | | | British Standard |
| Release characteristic | | | Other |
| Installation technique | | | Oil |