



Предохранитель двигателя, среднее напряжение, 125 А, AC 3.6 kV, 50 кА, 51 x 356 mm, резерв, BS, без бойка-индикатора

Тип **3.6KV 125Amp 2" 'F' MOTORSTART FUSE N/S**  
 Каталог № **3.6WDFNF125**

Abbildung ähnlich

## Программа поставок

Программа поставок			Предохранитель
Основная функция			Предохранитель двигателя
Область применения			среднее напряжение
Номинальный ток	I	A	125
Номинальное напряжение			AC 3.6 kV
Типоразмер			51 x 356 mm
Категория применения			резерв
Индикатор состояния			без бойка-индикатора
Отключающая способность		кА	50
возможно использование для типоразмеров/оборудования			защита двигателя
Стандарт/сертификат			BS
Форма			цилиндрический со смещенными винтовыми наконечниками
Стандарты/предписания			BS2692-1

## Технические характеристики согласно ETIM 7.0

Circuit breakers and fuses (EG000020) / Medium-/high voltage fuse (EC003507)			
Rated current		A	25
Rated voltage		kV	3.6
Voltage type			AC
Rated frequency		Hz	50 - 50
Breaking capacity		kA	50
Utilization category			Other
Application			Motor protection
Length		mm	254
Diameter		mm	51
Performance category according to IEC 60282-1			Back-up
With striker			No
Standard			British Standard
Release characteristic			Other
Installation technique			Air