



Воздушный предохранитель, среднее напряжение, 16 А, AC 15.5 kV, 20 кА, 461 x 50.8 mm, резерв, BS, без бойка-индикатора

Тип 15.5KV 16AMP 2" 'F' AIR FUSE N/S
Каталог № 15.5BDGNF16

Abbildung ähnlich

Программа поставок

Программа поставок			Предохранитель
Основная функция			Воздушный предохранитель
Область применения			среднее напряжение
Номинальный ток	I	A	16
Номинальное напряжение			AC 15.5 kV
Типоразмер			461 x 50.8 mm
Категория применения			резерв
Индикатор состояния			без бойка-индикатора
Отключающая способность		кА	20
возможно использование для типоразмеров/оборудования			защита первичной обмотки трансформаторов используется в сборках выключателя с предохранителем, держателях предохранителей и выключателях с предохранителем
Стандарт/сертификат			BS
Форма			цилиндрический с двойным корпусом
Стандарты/предписания			BS2692-1

Технические характеристики согласно ETIM 7.0

Circuit breakers and fuses (EG000020) / Medium-/high voltage fuse (EC003507)			
Rated current		A	16
Rated voltage		kV	15.5
Voltage type			AC
Rated frequency		Hz	50 - 50
Breaking capacity		kA	20
Utilization category			Other
Application			Primary side transformer protection
Length		mm	461
Diameter		mm	51
Performance category according to IEC 60282-1			Back-up
With striker			No
Standard			British Standard
Release characteristic			Other
Installation technique			Air