



Трансформатор тока 40/5 А

Тип Z-MG/WAK40
Каталог № 101619

Abbildung ähnlich

Технические характеристики согласно ETIM 7.0

Low-voltage industrial components (EG000017) / Current transformer (EC002048)			
Электротехника, электроника, системы автоматизации / Обработка сигналов / Transformer / Current transformer (ecl@ss10.0.1-27-21-09-02 [AAB626014])			
Model			Through-feed current converter
Primary rated current	A		40
Secondary rated current	A		5
Secondary rated apparent power	VA		0
Accuracy class			3
Over current limiting factor			FS 5
Calibrated			No
With shock protection			No
Height opening	mm		0
Width opening	mm		0
Opening diameter	mm		22
Snap mounting			Yes
With copper rail			No
Secondary connection			Plug-in connection
Number of primary inputs			1