



**Воздушный предохранитель, среднее напряжение, 16 А, AC 24 kV, 12 кА, 2", 51 x 565 mm, резерв, BS, с наклейкой**

**Тип** 24KV 16AMP 2" 'A' AIR FUSE  
**Каталог №** 24ADIHA16

Abbildung ähnlich

## Программа поставок

Программа поставок			Предохранитель
Основная функция			Воздушный предохранитель
Область применения			среднее напряжение
Номинальный ток	I	A	16
Номинальное напряжение			AC 24 kV
Типоразмер			2"
Типоразмер			51 x 565 mm
Категория применения			резерв
Индикатор состояния			с наклейкой
Отключающая способность		кА	12
возможно использование для типоразмеров/оборудования			защита первичной обмотки трансформаторов
Стандарт/сертификат			BS
Форма			цилиндрический
Стандарты/предписания			BS2692-1

## Технические характеристики согласно ETIM 7.0

Circuit breakers and fuses (EG000020) / Medium-/high voltage fuse (EC003507)			
Rated current		A	16
Rated voltage		kV	24
Voltage type			AC
Rated frequency		Hz	50 - 50
Breaking capacity		kA	12
Utilization category			Other
Application			Primary side transformer protection
Length		mm	565
Diameter		mm	51
Performance category according to IEC 60282-1			Back-up
With striker			Yes
Standard			British Standard
Release characteristic			Other
Installation technique			Air