



Воздушный предохранитель, среднее напряжение, 31.5 А, AC 12 kV, 12 кА, 51 x 356 mm, резерв, BS, без бойка-индикатора

Тип **12KV 31.5AMP 2" '6B' AIR FUSE N/S**
Каталог № **12ADFN6B31.5**

Abbildung ähnlich

Программа поставок

Программа поставок			Предохранитель
Основная функция			Воздушный предохранитель
Область применения			среднее напряжение
Номинальный ток	I	A	31.5
Номинальное напряжение			AC 12 kV
Типоразмер			51 x 356 mm
Категория применения			резерв
Индикатор состояния			без бойка-индикатора
Отключающая способность		кА	12
возможно использование для типоразмеров/оборудования			защита первичной обмотки трансформаторов используется в сборках выключателя с предохранителем, держателях предохранителей и выключателях с предохранителем
Стандарт/сертификат			BS
Форма			цилиндрический смещенные болтовые наконечники
Стандарты/предписания			BS2692-1

Технические характеристики согласно ETIM 7.0

Circuit breakers and fuses (EG000020) / Medium-/high voltage fuse (EC003507)			
Rated current		A	31.5
Rated voltage		kV	12
Voltage type			AC
Rated frequency		Hz	50 - 50
Breaking capacity		kA	12
Utilization category			Other
Application			Primary side transformer protection
Length		mm	254
Diameter		mm	51
Performance category according to IEC 60282-1			Back-up
With striker			No
Standard			British Standard
Release characteristic			Other
Installation technique			Air

Дополнительная информация о продуктах (ссылки)

Product catalogue (pdf)	http://www1.cooperbusmann.com/pdf/4c55bf59-424e-4973-bb95-bd162228cca8.pdf
-------------------------	---