



**Воздушный предохранитель, среднее напряжение, 3.15 А, АС 24 кV, 12 кА, 76 x 565 мм, резерв, BS, без бойка-индикатора**

**Тип** 24KV 3.15AMP 3" 'F' AIR FUSE N/S  
**Каталог №** 24AFINF3.15

Abbildung ähnlich

## Программа поставок

Программа поставок			Предохранитель
Основная функция			Воздушный предохранитель
Область применения			среднее напряжение
Номинальный ток	I	A	3.15
Номинальное напряжение			АС 24 kV
Типоразмер			76 x 565 mm
Категория применения			резерв
Индикатор состояния			без бойка-индикатора
Отключающая способность		кА	12
возможно использование для типоразмеров/оборудования			защита первичной обмотки трансформаторов
Стандарт/сертификат			BS
Форма			смещенные болтовые наконечники
Стандарты/предписания			BS2692-1

## Технические характеристики согласно ETIM 7.0

Circuit breakers and fuses (EG000020) / Medium-/high voltage fuse (EC003507)			
Rated current		A	3.15
Rated voltage		kV	24
Voltage type			AC
Rated frequency		Hz	50 - 50
Breaking capacity		kA	12
Utilization category			Other
Application			Primary side transformer protection
Length		mm	565
Diameter		mm	76
Performance category according to IEC 60282-1			Back-up
With striker			No
Standard			British Standard
Release characteristic			Other
Installation technique			Air