



**Воздушный предохранитель, среднее напряжение, 100 А, AC 7.2 kV, 40 кА, BS, 76 x 461 mm, резерв, BS, без бойка-индикатора**

**Тип** 7.2KV 100AMP 3" 'A' AIR FUSE N/S  
**Каталог №** 7.2BFGNA100

Abbildung ähnlich

## Программа поставок

Программа поставок			Предохранитель
Основная функция			Воздушный предохранитель
Область применения			среднее напряжение
Номинальный ток	I	A	100
Номинальное напряжение			AC 7.2 kV
Типоразмер			BS
Типоразмер			76 x 461 mm
Категория применения			резерв
Индикатор состояния			без бойка-индикатора
Отключающая способность		кА	40
возможно использование для типоразмеров/оборудования			защита первичной обмотки трансформаторов
Стандарт/сертификат			BS
Форма			цилиндрический
Стандарты/предписания			BS2692-1

## Технические характеристики согласно ETIM 7.0

Circuit breakers and fuses (EG000020) / Medium-/high voltage fuse (EC003507)			
Rated current		A	100
Rated voltage		kV	7.2
Voltage type			AC
Rated frequency		Hz	50 - 50
Breaking capacity		kA	40
Utilization category			Other
Application			Primary side transformer protection
Length		mm	359
Diameter		mm	76
Performance category according to IEC 60282-1			Back-up
With striker			No
Standard			British Standard
Release characteristic			Other
Installation technique			Air