



**Воздушный предохранитель, среднее напряжение, 31.5 А, AC 3.6 kV, 51 x 192 mm, резерв, BS, с наклейкой**

**Тип** 3.6KV 31.5Amp 2" '46' Air Fuse  
**Каталог №** 3.6AD0H4631.5

Abbildung ähnlich

## Программа поставок

Программа поставок			Предохранитель
Основная функция			Воздушный предохранитель
Область применения			среднее напряжение
Номинальный ток	I	A	31.5
Номинальное напряжение			AC 3.6 kV
Типоразмер			51 x 192 mm
Категория применения			резерв
Индикатор состояния			с наклейкой
возможно использование для типоразмеров/оборудования			защита первичной обмотки трансформаторов
Стандарт/сертификат			BS
Форма			цилиндрический со смещенными винтовыми наконечниками
Стандарты/предписания			BS2692-1

## Технические характеристики согласно ETIM 7.0

Circuit breakers and fuses (EG000020) / Medium-/high voltage fuse (EC003507)			
Rated current		A	31.5
Rated voltage		kV	3.6
Voltage type			AC
Rated frequency		Hz	50 - 50
Breaking capacity		kA	60
Utilization category			Other
Application			Primary side transformer protection
Length		mm	254
Diameter		mm	51
Performance category according to IEC 60282-1			Back-up
With striker			Yes
Standard			British Standard
Release characteristic			Other
Installation technique			Air