



**Воздушный предохранитель, среднее напряжение, 10 А, AC 14.3 kV, 200 кА, 3", 565 x 76.2 mm, резерв, BS**



Powering Business Worldwide™

**Тип** 14.3KV 10AMP 3" AIR FUSE  
**Каталог №** 14-3AFINF10  
**Alternate Catalog No.** 14.3AFINF10

Abbildung ähnlich

## Программа поставок

Программа поставок			Предохранитель
Основная функция			Воздушный предохранитель
Область применения			среднее напряжение
Номинальный ток	I	A	10
Номинальное напряжение			AC 14.3 kV
Типоразмер			3"
Типоразмер			565 x 76.2 mm
Категория применения			резерв
Отключающая способность		кА	200
возможно использование для типоразмеров/оборудования			защита первичной обмотки трансформаторов используется в сборках выключателя с предохранителем, держателях предохранителей и выключателях с предохранителем
Стандарт/сертификат			BS
Форма			цилиндрический с двойными смещенными болтовыми наконечниками
Стандарты/предписания			BS2692-1

## Технические характеристики согласно ETIM 7.0

Circuit breakers and fuses (EG000020) / Medium-/high voltage fuse (EC003507)			
Rated current		A	10
Rated voltage		kV	14.3
Voltage type			AC
Rated frequency		Hz	50 - 50
Breaking capacity		кА	200
Utilization category			Other
Application			Primary side transformer protection
Length		mm	565
Diameter		mm	76
Performance category according to IEC 60282-1			Back-up
With striker			No
Standard			British Standard
Release characteristic			Other
Installation technique			Air