

ТЕХНИЧЕСКИЙ ПАСПОРТ - 12KV 80AMP 88MM FULL RANGE FUSE



Предохранитель, среднее напряжение, 80 А, AC 12 kV, 3.5", 88 x 292 мм, полный диапазон, DIN, без бойка-индикатора



Тип **12KV 80AMP 88MM FULL RANGE FUSE**
Каталог № **12FXLNJ80**

Abbildung ähnlich

Программа поставок

Программа поставок			Предохранитель
Основная функция			Предохранитель
Область применения			среднее напряжение
Номинальный ток	I	A	80
Номинальное напряжение			AC 12 kV
Типоразмер			3.5"
Типоразмер			88 x 292 mm
Категория применения			полный диапазон
Индикатор состояния			без бойка-индикатора
возможно использование для типоразмеров/оборудования			Защита первичной обмотки трансформатора
Стандарт/сертификат			DIN

Технические характеристики согласно ETIM 7.0

Circuit breakers and fuses (EG000020) / Medium-/high voltage fuse (EC003507)			
Rated current		A	80
Rated voltage		kV	12
Voltage type			AC
Rated frequency		Hz	50 - 50
Breaking capacity		kA	50
Utilization category			Other
Application			Primary side transformer protection
Length		mm	292
Diameter		mm	88
Performance category according to IEC 60282-1			Full-range
With striker			No
Standard			DIN
Release characteristic			Other
Installation technique			Air