



**Воздушный предохранитель, среднее напряжение, 100 А, AC 12 kV, 40 кА, 3", 76 x 359 mm, резерв, BS, с наклейкой**

**Тип** 12KV 100AMP 3" '36' AIR FUSE  
**Каталог №** 12BFGH36100

Abbildung ähnlich

## Программа поставок

Программа поставок			Предохранитель
Основная функция			Воздушный предохранитель
Область применения			среднее напряжение
Номинальный ток	I	A	100
Номинальное напряжение			AC 12 kV
Типоразмер			3"
Типоразмер			76 x 359 mm
Категория применения			резерв
Индикатор состояния			с наклейкой
Отключающая способность		кА	40
возможно использование для типоразмеров/оборудования			защита первичной обмотки трансформаторов используется в сборках выключателя с предохранителем, держателях предохранителей и выключателях с предохранителем
Стандарт/сертификат			BS
Стандарты/предписания			BS2692-1

## Технические характеристики согласно ETIM 7.0

Circuit breakers and fuses (EG000020) / Medium-/high voltage fuse (EC003507)			
Rated current		A	100
Rated voltage		kV	12
Voltage type			AC
Rated frequency		Hz	50 - 50
Breaking capacity		kA	40
Utilization category			Other
Application			Primary side transformer protection
Length		mm	359
Diameter		mm	76
Performance category according to IEC 60282-1			Back-up
With striker			Yes
Standard			British Standard
Release characteristic			Other
Installation technique			Air

## Дополнительная информация о продуктах (ссылки)

Product catalogue (pdf)

<http://www1.cooperbusmann.com/pdf/4c55bf59-424e-4973-bb95-bd162228cca8.pdf>