



Воздушный предохранитель, среднее напряжение, 3.15 А, AC 24 kV, 12 кА, 2", 51 x 565 mm, резерв, BS, без бойка-индикатора

Тип 24KV 3.15AMP 2" 'B' AIR FUSE N/S
Каталог № 24ADINB3.15

Abbildung ähnlich

Программа поставок

Программа поставок			Предохранитель
Основная функция			Воздушный предохранитель
Область применения			среднее напряжение
Номинальный ток	I	A	3.15
Номинальное напряжение			AC 24 kV
Типоразмер			2"
Типоразмер			51 x 565 mm
Категория применения			резерв
Индикатор состояния			без бойка-индикатора
Отключающая способность		кА	12
возможно использование для типоразмеров/оборудования			защита первичной обмотки трансформаторов
Стандарт/сертификат			BS
Форма			смещенные болтовые наконечники
Стандарты/предписания			BS2692-1

Технические характеристики согласно ETIM 7.0

Circuit breakers and fuses (EG000020) / Medium-/high voltage fuse (EC003507)			
Rated current		A	3.15
Rated voltage		kV	24
Voltage type			AC
Rated frequency		Hz	50 - 50
Breaking capacity		kA	12
Utilization category			Other
Application			Primary side transformer protection
Length		mm	565
Diameter		mm	51
Performance category according to IEC 60282-1			Back-up
With striker			No
Standard			British Standard
Release characteristic			Other
Installation technique			Air